



Rep	Details of components	Dia.mm	Characteristics
1	4P * 22AWG with individual Drain Tin-coated copper Stranded wire : 0.26mm/7	0.78	<u>Electrical characteristics</u> Voltage : 300 Volts RMS Spark Test : 4,000V/0.15sec Insulation resistance : above 500Mohm.Km Conductor Resistance 22AWG : max 51.0 ohm/km 20AWG : max 37.5 ohm/km
2	3C * 20AWG Tin-coated copper Stranded wire : 0.30mm/7	0.90	
3	Insulation of 22AWG : TEFLON FEP BK vs. WH, GN, YL, BR	1.27	
4	Insulation of 20AWG : TEFLON FEP RD, BL, BK	1.50	<u>General characteristics</u> Operating temperature : -70 ~ 200℃ Outside Diameter : 7.8mm (± 0.70mm) Conductor Standard for IEC 60228-3 Standard cable color : RED (option) Cable net Weight : Approx. 36kg / 1,000Ft
5	Pair Shield with Drain : Al. foil-Polyester	2.7	
6	Out Jacket : TEFLON FEP Standard Color "RED"	7.8	

This Document belongs to "ZEUS ELECTRIC" and can not be used without his authorization.

D					
C					
B					
A	2017.07.25	Creation			SB, Lee
Revision	Date	Contents of Revision	Revised by	Verified by	Approved by